# **Product summary**

# MAX-M10 series

# P

# u-blox M10 standard precision GNSS modules

#### Ultra-low-power GNSS receiver for high-performance asset-tracking devices

- · Less than 25 mW power consumption without compromising GNSS performance
- · Maximum position availability with concurrent reception of 4 GNSS
- Proven excellent performance, even with small antennas
- Advanced spoofing and jamming detection
- Pin-compatible with previous MAX products







9.7 × 10.1 × 2.5 mm



### Product description

The MAX-M10 series is built on the ultra-low-power u-blox M10 GNSS platform, which provides exceptional sensitivity and acquisition times for all L1 GNSS systems.

The extremely low power consumption of less than  $25\,\mathrm{mW}$  in continuous tracking mode allows great power autonomy for all battery-operated devices, such as asset trackers, without compromising on GNSS performance.

MAX-M10 supports concurrent reception of four GNSS (GPS, GLONASS, Galileo, and BeiDou). The high number of visible satellites enables the receiver to select the best signals. This maximizes the position availability, in particular under challenging conditions such as in deep urban canyons.

u-blox Super-S technology offers great RF sensitivity and can improve the dynamic position accuracy by up to 25% with small antennas or in a non-line-of-sight scenario.

The MAX-M10S module integrates an LNA followed by an SAW filter in the RF path for maximum sensitivity in passive antenna designs. MAX-M10M offers a cost and power optimized setup without LNA and SAW filter.

MAX-M10 detects jamming and spoofing attempts and reports them to the host, so that the system can react to such events. Advanced filtering algorithms mitigate the impact of RF interference and jamming, thus enabling the product to operate as intended.

Both modules offer backwards pin-to-pin compatibility with previous u-blox generations, which saves designers time and cost when upgrading their designs.

	MAX-M10M	MAX-M10S
Grade		
Automotive		
Professional Standard	•	•
GNSS		
GPS + QZSS/SBAS	•	
GLONASS	•	•
Galileo	•	•
BeiDou	•	•
Number of concurrent GNSS	4	4
Interfaces		
UART	1	1
SPI		
DDC (I2C compliant)	1	1
Features		
Additional SAW		•
Additional LNA		•
RTC crystal	•	•
Oscillator	С	Т
Timepulse	1	1
Power supply		
1.8 V – 5.5 V	•	
2.7 V – 3.6 V		•
		0 111/7 70/0

C = Crystal / T = TCXO



## MAX-M10 series



#### **Product performance**

Receiver type

	GPS L1 C/A, QZS BeiDou B1I/B1C, SBAS L1 C/A: WA	Galileo E1B/C	
Nav. update rate	Up to 10 Hz (4 concurrent GNSS)		
Horizontal position accuracy	1.5 m CEP		
		MAX-M10M	MAX-M10S
Acquisition <sup>1</sup>	Cold start Aided start Hot start	26 s 3 s 1 s	24 s 2 s 1 s
Sensitivity <sup>1</sup>	Tracking & Nav. Reacquisition Cold start	–164 dBm –161 dBm –148 dBm	–167 dBm –161 dBm –148 dBm

u-blox M10 engine

#### **Tracking features**

u-blox Super-S	Improved accuracy with small antennas
Data batching	Autonomous tracking up to 10 min at 1 Hz
Odometer	Measure traveled distance with support for different user profiles

–159 dBm

-159 dBm

Hot start

#### Security features

Signal integrity	RF interference & jamming detection and reporting Active GNSS in-band filtering Spoofing detection and reporting
Device integrity	Receiver configuration lock by command
Secure interface	Signed UBX messages (SHA-256) JTAG debug interface disabled by default

#### Electrical data

	MAX-M10M	MAX-M10S
Power supply	1.8 V to 5.5 V	2.7 V to 3.6 V
Power consumption at 3 V	2 GNSS: 19 mW 3 GNSS: 23 mW <sup>1</sup> 4 GNSS: 27 mW	2 GNSS: 24 mW 3 GNSS: 28 mW <sup>1</sup> 4 GNSS: 32 mW
Backup supply	1.65 V to 3.6 V	1.65 V to 3.6 V

<sup>1 =</sup> For continuous tracking in default mode: GPS/BeiDou/Galileo + SBAS/QZSS

#### **Package**

18 pin LCC (Leadless Chip Carrier): 9.7 × 10.1 × 2.5 mm, 0.6 g

#### Environmental data, quality & reliability

Operating temp.	-40 °C to +85 °C
Storage temp.	-40 °C to +85 °C
Environmental grade	2015/863/EU RoHS-3
EMC (electromagnetic compatibility)	2014/53/EU RED
Environmental testing	ISO 16750
Quality management	Manufactured and fully tested in IATF 16949 certified production sites

#### Interfaces

meoriadoo	
Serial interfaces	1 UART 1 DDC (I2C compliant)
Digital I/O	Configurable timepulse 1 EXTINT input for Wakeup
Raw Data output	Code phase data
Timepulse	Configurable: 0.25 Hz to 10 MHz
Supported antennas	Active and passive
Protocols	NMEA 4.10, UBX binary

#### Services

Assisted GNSS	AssistNow GNSS Online: Data valid 2-4 hours
	AssistNow GNSS Offline: Data valid up to 35 days
	AssistNow Autonomous: Data valid up to 6 days
	OMA SUPL & 3GPP compliant

#### Support products

EVK-M101	u-blox M10 GNSS evaluation kit with UBX-M10050-KB chip and I/O interface
u-center	Highly interactive and easy-to-use GNSS evaluation software

#### **Product variants**

MAX-M10M	u-blox M10 concurrent GNSS LCC module, firmware in ROM, crystal oscillator
MAX-M10S	u-blox M10 concurrent GNSS LCC module, firmware in ROM, SAW filter, LNA, TCXO

#### NOTE:

This document provides an objective specification overview of this product. Please refer to the data sheet for details on firmware-related performance and feature support.

#### Further information

For contact information, see **www.u-blox.com/contact-u-blox**. For more product details and ordering information, see the product data sheet.

#### Legal Notice:

u-blox reserves all rights to this document and the information contained herein. Products, names, logos and designs described herein may in whole or in part be subject to intellectual property rights. Reproduction, use, modification or disclosure to third parties of this document or any part thereof without the express permission of u-blox is strictly prohibited.

The information contained herein is provided "as is". No warranty of any kind, either express or implied, is made in relation to the accuracy, reliability, fitness for a particular purpose or content of this document. This document may be revised by u-blox at any time. For most recent documents, please visit www.u-blox.com.